

**PIN 31 R129 - Infrared Remote Control for Central Locking**

- 1 No fault
- 2 IRCL Control Module
- 3 Supply pump, central locking system short to ground
- 4 Infrared remote control receiver, Left front door/Right front door/ Trunk lid Red indicator lamps, short to ground
- 5 Infrared remote control receiver, Left front door/Right front door/ Trunk lid Green indicator lamps, short to ground
- 6 Supply pump, central locking system, short to B (+)
- 7 Infrared remote control receiver, left front door/Right front door/Trunk lid Red indicator lamps, short to B(+) or open circuit
- 8 Infrared remote control receiver, left front door/Right front door/Trunk lid Green indicator lamps, short to B(+) or open circuit
- 9 Driver door switch group wiring, short to B (+) ATA/CF microswitch wiring short to B(+) ATA/CF wiring short to B(+)
- 10 Ignition/starter switch-position recognition switch open circuit
- 11 Ignition/starter switch-position recognition switch open circuit 31
- 12 Left front door actuator, open circuit
- 13 Right door actuator, open circuit
- 14 Trunk lid lock actuator, open circuit
- 15 Immobilization output, short to B(+)